



Radio Controls and Indicators

Talk Button

Press and hold to communicate with others. With the microphone about five cm (2 inches) from your mouth, speak in a normal voice.

Release the **Talk** button when you are finished talking and listen for a response. You cannot receive incoming calls while pressing the **Talk** button.

NOTE Both radios must be tuned to the same channel to communicate.



Call Button

Press and release to alert others that you are calling.

Speaker/
Microphone/
Charge Jack

LCD
Display

Up/Down Buttons

Press and release to adjust the volume.

While in mode function, press and release to change channels.

Mode/Power Button

Press and hold to turn the radio **on** or **off**.

Press and release to enter mode function to change channels. The channel numbers will blink when that mode is selected. Use the **Up/Down** buttons to select a channel.



TWO-WAY RADIO MODEL MT245VP

Printed in China
Part No. 480-867-P
Version D

Nothing Comes Close to a Cobra®

English



Batteries and Charging



NOTE: Excessive sound pressure from earphones and headphones can cause hearing loss.

Batteries

Remove Belt Clip



Pull Latch Up



Insert Batteries



To install or replace batteries:

1. Remove belt clip by releasing belt clip latch and sliding clip up.
 2. Pull up on the battery door latch to remove the battery compartment cover.
 3. Insert the supplied three AAA rechargeable batteries (also works with non-rechargeable alkaline batteries). Position batteries according to polarity markings.
 4. Replace battery compartment cover and belt clip.
- Do not attempt to charge alkaline batteries.
 - Do not mix old and new batteries.
 - Do not mix alkaline, standard (carbon-zinc), or rechargeable (Ni-Cd, Ni-MH, etc.) batteries.
 - The radio is not intended to be used while being charged.

Maximum/Minimum Operating Range: -20°C to +45°C

Caution – Risk of explosion if battery is replaced by an incorrect type. Dispose of used batteries according to the instructions.



LCD Display

Channel Number

While in **Standby** mode or when selecting a channel, shows current channel (1 through 8).

When adjusting the volume, shows current level (1 through 8).



Receive Icon

Visible when receiving a message.

Transmit Icon

Visible when transmitting a message.

Battery Low Icon

Blinks when battery power level is low.

Your microTALK® radio has a unique circuit designed to extend battery life. If there are no transmissions within 10 seconds, the radio will automatically switch to **Battery Save** mode. This will not affect the radio's ability to receive incoming transmissions.

Channel/Volume Indicator

"CH" is visible when in **Standby** mode or when selecting a channel.

"LE" is visible when adjusting volume.



R&TTE Declaration of Conformity (DoC) / Warranty & Customer Service

We, Cobra Electronics Europe Limited of
Dungar House, Northumberland Avenue
Dun Laoghaire, County Dublin, Ireland

declare under our sole responsibility that the
product: **Private Mobile Radio (PMR 446)**

Model: MT 245

to which this declaration relates is in conformity
with the essential requirements and other relevant
requirements of the R&TTE Directive (1999/5/EC).

The product is in conformity with the following
standards and/or other normative documents:

Health (Article 3.1(a)): **EN 62311 (2008)**

Safety (Article 3.1(a)): **EN 60950-1:2006/A12:2011**

EMC: (Article 3.1(b)): **EN 301 489-1 V1.9.2 (2011-09)**

EN 301 489-5 V1.3.1 (2002-08)

Spectrum (Article 3.2): **EN 300 296-2 V1.4.1 (2013-08)**

This product complies with Commission Regulation
(EC) No 278/2009 of 6 April 2009 implementing
Directive 2009/125/EC of the European Parliament and
of the Council with regard to ecodesign requirements
for no-load condition electric power consumption and
average active efficiency of external power supplies
and is in conformity with Directive 2011/65/EU of the
European Parliament and of the Council of 8 June
2011 on the restriction of the use of certain hazardous
substances in electrical and electronic equipment.

The radio will not comply with the standard at voltage
below 3.4V.

CE0168

DUBLIN, IRELAND 1 October 2014

MARK CLOSE
Managing Director

Warranty & Customer Service

For warranty and customer service
information, please contact your
local dealer.

For use in EU countries, subject to local laws
and regulations.

CEEL™ is a trademark of
Cobra Electronics Corporation, USA.

Snake design and microTALK® are registered
trademarks of Cobra Electronics Corporation, USA.

©2014 Cobra® Electronics Europe Limited
Dungar House, Northumberland Avenue
Dun Laoghaire, County Dublin, Ireland

www.cobra.com

